



## Idea: Dimmer 120V 30-500W/30-300VA white

### 16557.B

Idea / Devices / Electronic devices

### Dimmer 120V 30-500W/30-300VA white

Dimmer, 120 V~ 50-60 Hz, for: 30-500 W incandescent lamps, 30-300 VA ferromagnetic transformers, control and regulation by rotary potentiometer, visible in darkness, white

### Product Status

3 - Active

### Minimum order quantity


20 NR

### Sheets, Manuals, Documentation


- [Multilanguage instructions sheet \(542 kb\)](#)




## Drawings



Space view



Backside view



3D View

## Technical data

- **Class group:** Domestic switching devices
- **Class:** Dimmer
- **Method of operation:** Turn button
- **Type of load:** Inductive load
- **Applicable with button:** No
- **Applicable with movement sensor:** No
- **Applicable with presence indicator:** No
- **Applicable with time switch/timer:** No
- **Applicable with transmission button:** No
- **Applicable with infrared button:** No
- **Mounting method:** Flush mounted (plaster)
- **Type of fastening:** Snapper mounting
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Surface protection:** Untreated
- **Surface finishing:** Matt
- **Colour:** White
- **RAL-number (similar):** 9001
- **Transparent:** No
- **Suitable for degree of protection (IP):** IP40
- **Nominal voltage:** 120,00 - 120,01 v
- **Frequency:** 50,00 - 60,00 HZ
- **Control voltage:** 120,00 - 120,01 v
- **Width of device:** 24,80 mm
- **Height of device:** 50,10 mm
- **Depth of device:** 58,20 mm

## Certifications

- 00. CE Marking - EU
- 10. EAC Eurasian Customs Union
- 19. NOM - Mexico
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 99. WEEE Directive ([download](#))

## Packaging



**Code** 8007352146471  
**Quantity** 1 NR  
**Dim.** 5.3x3.9x7.6 [cm]  
**Weight** 48.47 [g]



**Code** 8007352146488  
**Quantity** 20 NR  
**Dim.** 28.1x13.1x11.3 [cm]  
**Weight** 1,075.53 [g]

## Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).